

Dwi Astuti Cahyasiwi - Orthogonal Resonators for Circularly Polarized Filtering Antenna Using A Single Feedline

by Dwi Astuti Cahyasiwi Uploaded By Lutfan Zulwaqar

Submission date: 01-Apr-2023 05:34PM (UTC+0700)

Submission ID: 2052805171

File name: similarity_check.pdf (1.18M)

Word count: 6177

Character count: 31790

Orthogonal Resonators for Circularly Polarized Filtering Antenna Using A Single Feedline

3 Dwi Astuti Cahyasiwi, Member, IEEE, Fitri Yuli Zulkifli, Senior Member, IEEE, and Eko Tjipto Rahardjo, Member, IEEE

Abstract— Polarization diversity is an antenna feature that has been widely researched to increase the capacity of a wireless communication system. The conceptual theory of polarization states that all polarization vectors can be decomposed into two orthogonal electric field vector modes. This study proposes a novel framework to bridge the gap between circular polarization technique and filtering antenna design using two orthogonal resonators with the ability to represent any polarization. The proposed method combines the techniques of antenna-filter and circular polarization design into a single integrated step. To achieve second-order antenna-filter integration and generate circular polarization, the two orthogonal resonators modeled as a rectangular radiator and a $\lambda/4$ resonator combined. The circular polarization filtering antenna operates at a frequency of 4.65 GHz, with an impedance bandwidth of 4.7%, axial ratio bandwidth of 3.2%, and a gain of 6.2-dBi. To validate the circular polarization filtering antenna, simulations and measurements were performed, and the results were found to be in good agreement.

13 **Index Terms**— Circular polarization, filtering antenna, interdigital, orthogonal resonator

13 I. INTRODUCTION

CIRCULARLY polarized antennas have been developed using various methods. The main principle that distinguishes antennas with linear and circular polarization is the $\pm 90^\circ$ phase difference between two orthogonal magnetic fields. Some techniques for generating circular polarization have been studied [1], [2]. A single feed technique intervenes the radiator to create two electromagnetic field modes with a 90° phase delay. This technique can be achieved using truncated and perturbation radiator elements [2]–[14]. The simplest method to achieve two orthogonal modes is to insert two orthogonal feeders [15]–[18]. However, as previously stated, two equal orthogonal fields will only generate circular polarization if there is a 90° phase difference, so this technique requires an additional phase delay circuit. The cancellation circuits to generate delay have been reported in [19]–[26], and some of the circuit has been applied to obtain circular polarization [18], [27].

The integration of a filter and antenna known as filtering antenna is advanced because of its controllable bandwidth

8 “This work was supported in part by Seed Funding Professor 25: NKB-1938/UN2.F4.D/PPM.00.00/2022” (Corresponding author: Eko Tjipto Rahardjo).


Dwi Astuti Cahyasiwi is with Electrical Engineering Department, Universitas Muhammadiyah Prof. Dr. HAMKA (email: dwi.cahyasiwi@uhamka.ac.id)

impedance. Furthermore, it performs a frequency selectivity with its bandpass-like response gain. The most common method to design a filtering antenna is to create a filter network using a radiator at a resonator. In a co-design technique, the antenna replaces the last stage resonator of the filter. Circular polarization (CP) filtering antennas have been studied using a single feedline [3], [4] and two orthogonal feedlines [17], [28], [29]. A truncated radiator generates CP, and a filtering circuit is added to provide selectivity features [3].

The filtering antennas create two orthogonal feedlines and 90° a phase delay circuit using a $\lambda/4$, $\lambda/2$ and two parallel $\lambda/2$ stub resonators [17], [28], [29]. Dispersive delay lines are added to one of the two orthogonal feedlines to obtain a circularly polarized filtering antenna [18]; their function is as filtering and delay circuits. All the extra components and two-step designs in the previous studies result in a bulky circuit.

In our previous studies, we developed 75° , 45° and; vertical polarization filtering antenna using the $\lambda/4$ resonator and a rectangular radiator [30]–[32]. In [31] the interaction between the radiator and resonator stimulates a second mode on the radiator and results in two orthogonal modes with a single feedline; additionally, with proper radiator size, 0° and 180° phase delay using a cancellation circuit in [22], the design generated 45° polarization. Based on the common characteristics of 45° polarization and CP, a circularly polarized antenna with a similar structure as in [31] can be designed by adding 90° phase delay. To the best of our knowledge, no technique on filtering antenna uses its integration process to generate CP, have been reported. Therefore, this study proposes a technique for designing a circularly polarized filtering antenna using single feedline that provides two orthogonal modes and 90° delay without an additional circuit or radiator perturbation. The proposed technique simplifies the design process of CP filtering antenna from two steps to one step. This method merges the antenna-filter integration and polarization generator technique. Furthermore, it applies to generate linear and CP. Characteristics of CP are proven with $|E_\theta|/|E_\phi|$, phase difference (δ_λ) and axial ratio (AR) parameters, within the bandwidth operational. Selectivity performance is represented with the gain over the operational bandwidth. This paper is organized as follows; Section II explains the proposed

6 Fitri Yuli Zulkifli and Eko Tjipto Rahardjo are with Antenna and Microwave Research Group (AMRG) Electrical Engineering Department, Faculty of Engineering, Universitas Indonesia (e-mail: eko@eng.ui.ac.id).



42
Fig. 1. Concept of the proposed antenna and its equivalent circuit

method for CP excitation using two orthogonal resonators based on the general polarization theory. Section III describes the antenna-filter integration. Section IV presents the result and discussion. Finally, the results are concluded in Section V.

II. PROPOSED METHOD


Polarization is a relation of the electrical fields in θ and Φ in the spherical coordinate system, as expressed in (1),

$$\vec{E} = E_{\theta}\cos(\omega t)\hat{\theta} + E_{\Phi}\cos(\omega t + \delta_L)\hat{\Phi}, \quad (1)$$


which explicates that total electrical field, \vec{E} , can be decomposed into two virtual orthogonal electrical field vectors in $\hat{\theta}$ (E_{θ}) and $\hat{\Phi}$ (E_{Φ}) directions [33]. Any polarization can be represented by two orthogonal linear polarizations (E_{θ} and E_{Φ}). In general, the magnitudes of these fields can be different or equal, and they may be in-phase or out of phase by an angle δ_L . If δ_L is 0° or 180° , it is linear, whereas, if δ_L is $+90^\circ$ or -90° , it is circular. Hence, from the theoretical framework above, these two virtual orthogonal electrical fields can be realized, with two individual structures represented by vertical and horizontal surface currents.

$$|E_{\theta}| = |E_{\Phi}| \quad (2)$$

The physical construction of the proposed method can be represented using the two orthogonal resonant structures as shown in Fig 1, where a $\lambda/4$ resonator (L_1, C_1) represents e-field in the $\hat{\theta}$ direction, with a horizontal surface current along the x -axis to excite second mode on the radiator, which is orthogonal to the radiator surface current. The gap between $\lambda/4$ resonator and radiator offers a 90° phase delay in addition to coupling between resonator and rectangular radiator. Using this gap, no additional delay circuit is required. The radiator (L_2, C_2 , and R_2) represents e-field in the $\hat{\Phi}$ direction, with vertical surface current along the y -axis. The gap between the $\lambda/4$



3
Fig. 2. Impure vertical polarization filtering antenna based on (a) third-order and (b) second-order filter [32].



10
Fig. 3 (a) Impure 75° slant polarization [30] and (b) 45° polarization [31].

resonator and radiator, as well as the length and width of the radiator, balanced the magnitude of the orthogonal modes. Finally, these structures are integrated to realize a total electrical field that accomplishes linear polarization or CP using a single port.

In the case of CP, the magnitude of the two electrical fields must be equal, as in (2), and the phase difference, δ_L , is 90° and -90° for left-hand and right-hand circular polarization, respectively. The equivalence between the two-magnitude e-fields in this method is determined by the ratio of the radiator's length (L_p) and width (W_p). While in the conventional filtering antenna, the ratio between L_p and W_p determines the radiator's radiation quality (Q_{rad}), which should be equal to the external quality (Q_{ext}) of the resonator. In the proposed method, the antenna-filter integration is applied by steering the ratio of W_p and L_p near 1, implying that Q_{rad} is not always equal to Q_{ext} . Besides the equal magnitude between the orthogonal e-fields, we have to provide a 90° phase delay between E_{θ} and E_{Φ} by increasing the radiator and resonator gap (C_B), thereby weakening E_{θ} . To maintain an equal ratio between the two fields, E_{θ} is strengthened by nearly equalizing W_p and L_p size while maintaining the same resonance frequency.

Previous studies have validated that W_p and L_p size and the gap between the orthogonal resonators are the main variables, determining the polarization [30]–[32]. As shown in Fig. 2 (a) and (b), the two designs based on third- and second-order filter

> REPLACE THIS LINE WITH YOUR MANUSCRIPT ID NUMBER (DOUBLE-CLICK HERE TO EDIT) <




Fig. 4 (a) Geometry and side view of Antenna I with unit dimension in mm and (b) 3D-view

using a narrow rectangular radiator, resulted in impure vertical polarization [32]. Meanwhile, Fig. 3(a) shows using wider W_p than the two previous design introduces stronger magnitude e -field in $\hat{\theta}$ direction [3] thus pulls the polarization to impure 75° slant. Furthermore, in Fig. 3(b), removing the gap between the radiator and interdigital resonator followed by equalizing the e -field in $\hat{\phi}$ and $\hat{\theta}$ with widening W_p , forms 45° polarization [31].

The following section presents an antenna-filter integration adaptation to excite circularly polarized filtering antenna using two orthogonal resonators to validate the proposed method.

III. ANTENNA-FILTER INTEGRATION

A. Antenna Geometry

This section presents a geometric structure of the optimized filtering antenna using a new method for CP excitation. The design uses second-order antenna-filter integration [24] and focuses on CP excitation. The geometric structure of the filtering antenna, as shown in Fig. 4(a), comprises a $17.4 \text{ mm} \times 19.2 \text{ mm}$ rectangular patch radiator proximity coupled with an $\lambda/4$ resonator. The gap between the rectangular radiator and resonator (C_B) is 3.6 mm . The width of the $\lambda/4$ resonator is 2.4 mm , and the approximated length of $\lambda_g/4$ is 10.8 mm ; it is also coupled with $50\text{-}\Omega$ transmission lines using a 0.7-mm gap. To generate a horizontal surface current, a through-hole of 1.2-mm diameter is attached on the left arm of the resonator. The antenna is printed on a $45 \text{ mm} \times 45\text{-mm}$ double layers Roger Duroid 5880 substrate with a thickness of 1.575 mm and




Fig. 5. Two individual structures comprising (a) an interdigital with hole extracted using two ports with a horizontal surface current (I), (b) a rectangular radiator with coupled feed that has a vertical surface current, and (c) the integration of two previous structures for left-hand circularly polarized filtering antenna. All structures resonant at 4.65 GHz .

permittivity of 2.2 . Fig. 4(b) shows the two-layers antenna (3D view), comprising of a radiator printed on the first substrate, resonator, and $50\text{-}\Omega$ feedline on the second substrate, and ground at the bottom.

B. Design Process

First, we realize this design starting from the conventional filtering antenna extraction method to obtain the resonance frequency. The resonator and radiator as the first and second mode generator, respectively, are extracted using two ports and they must have a matching resonant. As shown in Fig. 5(a), the first mode generator is embodied by the resonator's surface current along the x -axis. This current flows from the open circuit resonator's arm to the short circuit resonator's arm. The rectangular radiator's surface current initially generates a vertical surface current along the y -axis as the second mode as shown in Fig. 5(b). These two modes are integrated adapting the antenna-filter integration, and using the appropriate rectangular radiator size to obtain circular polarization, depicted in Fig. 5(c). The designs of the conventional filtering antenna (Ant I) and the proposed method (Ant II) are compared to prove the novelty of the new method. All design simulations and investigations are performed using CST tools.

The conventional filtering antenna is designed on the basis of a second-order Chebyshev filter with 4.65-GHz operational frequency, 0.1-dB ripple, 4.15% fractional bandwidth, as well as the low-pass parameters of $g_0 = 1$, $g_1 = 0.843$, $g_2 = 0.622$, and $g_3 = 1.3544$. The quality external factor (Q_{ext}) and coupling ($M_{i,i+1}$) obtained using (3) and (4) are 17.8 , and 0.051 , respectively.

$$Q_{\text{ext}} = \frac{g_n g_{n+1}}{FBW} \quad (3)$$

> REPLACE THIS LINE WITH YOUR MANUSCRIPT ID NUMBER (DOUBLE-CLICK HERE TO EDIT) <




Fig. 6 (a) Q_{rad} with the variation in W_p , (b) L_p variations with $W_p = 17.4$ under different resonance conditions, (c) $\lambda/4$ frequency resonant with various L_v , (d) Q_{ext} with variation in L_c [31] and (e) coupling with various in C_B (unit dimensions in mm)

$$M_{i,i+1} = \frac{FBW}{\sqrt{g_i g_{i+1}}} \quad (4)$$

$$Q_{rad} = \frac{f_o}{\Delta f} \quad (5)$$

The rectangular radiator are extracted using (5) to achieved Q_{rad} , where the Δf is 3-dB bandwidth and f_o is the center frequency.

The rectangular patch dimension described in Fig. 6(a) shows that 4.65-GHz resonance can be achieved using two $L_p \times W_p$ variations. The difference between these variations is the value of Q_{rad} . If the ratio of L_p to W_p is close to one, Q_{rad} will be decreased and reversed. Based on the extraction of conventional filtering antenna, Ant I's Q_{rad} should be 17.8, with $L_p \times W_p$ around 21 mm \times 4 mm. However, the ratio between L_p and W_p is steered to be equal using the proposed method in Ant II, as shown in Section II. Then, we used an $L_p \times W_p$ of 19 mm \times 18 mm, which resonates at 4.65 GHz with Q_{rad} of 8.3 to balance the E_θ and E_ϕ strength. A parametric study of L_p variations to




Fig. 7. Filtering antenna, Antenna I based on the second-order filter with vertical polarization, Antenna II adapting second-order filter with circular polarization




Fig. 8. Simulation of S_{11} and gain result for both designs

$$M_{n,n+1} = \frac{f_{n+1}^2 - f_n^2}{f_{n+1}^2 + f_n^2} \quad (6)$$

obtain 4.65-GHz resonance is shown in Fig. 6(b). The $\lambda/4$ resonance frequency extraction is performed similarly to [31], where the length of the resonator and through-hole position (L_v) are used to determine the resonant frequency. The $\lambda/4$ resonator obtains a 4.65-GHz resonant using a 10.8-mm arm's length with 9.5-mm L_v as shown in Fig.6(c).

The Q_{ext} of 17.8 is obtained when the gap between the $\lambda/4$ resonator and coupled feed (L_c) is near 1.1 mm using the conventional filtering antenna extraction method for Ant. I as shown in Fig. 6(d). The gap between the resonator and patch radiator (C_B) is ~ 4.3 mm to obtain a 0.051 coupling using (6), as described in Fig. 6(e). While for Ant. II, L_c is set to be minimum to strengthen E_θ , and C_B is set to provide a 90° phase difference between E_θ and E_ϕ . Different from the conventional filtering antenna design in Ant I that performs external quality between the resonator and the coupled feed, in Ant II, we set L_c in a range of 0.5–0.8 mm because this distance does not significantly affect polarization. However, it affects S_{11} response; thus, we need this parameter to adjust the impedance.

IV. RESULTS AND DISCUSSION

This section discusses the comparison results of the




Fig. 9 Axial ratio results of Ant. I and Ant. II






Fig. 10. Efficiency of Ant. I and Ant. II

conventional filtering antenna represented by Ant I and the newly proposed method represented by Ant II. The S_{11} and gain response of both designs are compared to the conventional antenna without filtering structure to understand the effect of the resonator addition and the new proposed method novelty. The parametric study and the measurement results of Ant II are presented to validate the proposed method.

C. Comparison Results of Ant I and Ant II

Applying the above procedure, we obtain an optimized design of the conventional and circularly polarized filtering antenna. Figure 7 shows the schematic design of the two filtering antennas. The conventional filtering antenna represented by Ant I has a narrower W_p than Ant II and a marginally longer L_p than Ant II. Fig. 8 shows the S_{11} and gain response of both designs. The S_{11} response in Ant I represents the second-order filter with two returns to zero and a single peak, whereas S_{11} of the proposed method in Ant II has a single resonant, as in a conventional antenna. This result is due to Ant II's omitted filtering antenna procedure, which should have a certain coupling value (0.051) between the radiator and resonator. The Q_{ext} and Q_{rad} equalization in Ant II were also excluded, resulting in the S_{11} filtering antenna with only a single minimal response.

Both antennas' center frequency is 4.65 GHz, and the -10 dB bandwidth impedance is 246 and 224 MHz for Ant I and Ant II, respectively. Ant I achieves its fractional bandwidth of 5.2% or 0.5% wider than the target value and two minimum S_{11} values of -16 dB at 4.57 GHz and -15.6 dB at 4.7 GHz. Ant II obtains

Fig. 11. S_{11} and gain parameter comparison of Ant I and Ant II to the conventional antennaFig. 12. Ratio magnitude E_0 to E_ϕ and phase difference of Ant. II

4.8% fractional bandwidth with S_{11} minimum value of -24.4 dB at 4.634 GHz. The gain response of Ant I shows a lower peak value but sharper shape than that in Ant II, and this is because the conventional extraction mainly focuses on the antenna's selectivity. A maximum gain of 5.77 dBi is achieved at 4.7 GHz for Ant. I, whereas Ant II shows a maximum gain of 6.46 dBi at 4.65 GHz or 0.69 dBi higher than the previous design. Figure 9 shows that Ant. I does not generate circular polarization from its high AR; in contrast, Ant II shows a 3-dB AR bandwidth of 150 MHz in a range of 4.575–4.725 GHz and attain the lowest value of 0.45 dB at 4.65 GHz. The radiator's width affects the efficiency of both antennas, where Ant. I with the narrower rectangular patch has less efficiency than Ant. II. The Ant. I's and Ant's II maximum efficiency is ~75% and 80% respectively as shown in Fig.10 and both designs have a bandpass-filter-like response. The results of Ant I and Ant II compared to the conventional antenna without filter integration are shown in Fig. 11. Ant I shows the sharpest gain response and widest frequency compared to Ant II and the conventional antenna. Ant II has the highest gain response among the other two designs and a sharper shape than the conventional antenna. It is proven that the resonator affects selectivity in Ant II, although it is not mainly focused on gain selectivity but also on the CP characteristic. Ant II also has equal bandwidth to the conventional antenna. Other parameters to prove the CP

> REPLACE THIS LINE WITH YOUR MANUSCRIPT ID NUMBER (DOUBLE-CLICK HERE TO EDIT) <




Fig. 13 Axial ratio and S_{11} response vary under different L_c (all unit dimensions are in mm)




Fig. 14. Axial ratio and S_{11} response vary under different C_B with constant W_p and L_p (all unit dimensions in mm)

characteristic in Ant II, as explained in (1) and (2), are the magnitude ratio between E_θ excited from the $\lambda/4$ resonator and E_ϕ excited from the rectangular radiator, as shown in Fig. 12. It shows that $|E_\theta|/|E_\phi|$ along the bandwidth ranges between 1.7 and 1.09 or near the theoretical value of 1, whereas phase differences are between -83° and -98° or near the ideal value of -90° . Those values indicate that Ant II has a left-hand CP.

D. Parametric Study of Ant II

The response of AR under different W_p has been proven in Ant I and Ant II, which is heavily related to the magnitude of E_θ and E_ϕ . Next, the effects of the gap space between the resonator and rectangular radiator (C_B) and the gap between the resonator and coupled feed are investigated in Ant II. Fig. 13 shows that in Ant II, the AR is unaffected by the gap between the resonator and coupled feed (L_c). It shows that S_{11} is optimum when L_c is 0.7 mm because, with less or more distance with an increment of 0.3 mm, its value increases; contrast to the AR, which is unaffected by L_c . In Ant II, the gap between the radiator and resonator (C_B) affects the axial ratio and S_{11} . Fig. 14 shows that with an increment of 1 mm, the S_{11} response and axial ratio are altered. The AR is minimum when C_B value is




Fig. 15. Photograph of Ant II (a) integrated layers (b) radiator patch (c) feeding structure




Fig. 16. S_{11} measurement result of Ant II

3.6 mm because if it is less or more, the AR and S_{11} increase. All parametric studies are conducted with constant W_p and L_p . C_B is an essential parameter for differentiating 45° linear polarization and CP in the proposed method because widening C_B will contribute 90° delay, whereas minimizing C_B to 0 mm will produce 0° or 180° delay between E_θ and E_ϕ , as performed in [31].

E. Measurement Result

To validate the proposed method, Ant II is fabricated and measured. Fig. 15 shows the photograph consisting of the assembled antenna in Fig. 15(a), the radiator layer in Fig. 15(b), and the feeding network in Fig. 15(c). S_{11} result is depicted in Fig. 16, where the simulation and measurement results have a good agreement. The measured frequency range of the proposed circularly polarized filtering antenna with $S_{11} < -10$ dB is 4.520–4.756 GHz, which shifts to a higher frequency and 4.8% wider than the simulation result. Its S_{11} gets the lowest value of -25 dB at 4.41 GHz, which is 4 dB higher than the simulated results. The 3-dB AR bandwidth measurement result shown in Fig. 17 is 100 MHz in a range of 4.633–4.733 GHz, which is 30% narrower than the simulation result. The lowest axial ratio is better than the simulation by 0.33 dB but shifts to 4.68 GHz. The insignificant discrepancy between the measured and simulated results is attributed to the assembly and fabrication tolerance. The gain measurement result depicted in

> REPLACE THIS LINE WITH YOUR MANUSCRIPT ID NUMBER (DOUBLE-CLICK HERE TO EDIT) <




Fig. 17. Axial ratio measurement result of Ant II at $\phi = 0^\circ$ and $\theta = 0^\circ$




Fig. 18. Gain measurement of Ant II

Fig. 18 shows a bandpass response along the bandwidth with a maximum value of 6.7 dBi at 4.65 GHz or 0.3 dB higher than the simulation result. The selectivity at the lower frequency is better than the upper frequency.

The measurement gain shows a sharper response than the simulation due to the simulation gain samples did not capture the dips that always arises in the filtering antenna measurement. The normalized radiation pattern measurement at 4.68 GHz is shown in Fig. 19. It shows a unidirectional pattern with the main lobe direction at 0° and -3 dB beamwidth of 80.5° and 81.5° at $\phi = 0^\circ$ and 90° respectively. The cross-polarization discriminant




Fig. 19. Normalized radiation pattern Ant II at 4.68 GHz

in the main lobe is higher than 30 dB for $\phi = 0^\circ$ and 90° , which agrees well with the simulation results.

Table 1 compares the proposed and previous methods, demonstrating that using a single feedline with an orthogonal resonator eliminates the need for an additional delay and filtering circuit. Reference [3] employs a single feedline with circular radiator perturbation, having the broadest AR bandwidth because it used a dipole antenna and a tradeoff with the lowest gain. The highest gain value was obtained in [12]–[14] using truncated radiator or radiator perturbation but with compensation for the size of the antennas. Some previous studies used two orthogonal feedlines to produce a broader AR bandwidth than the proposed method [16]–[18]. Although the proposed method had the narrowest AR bandwidth, it had the highest gain without extra circuit to produce CP and selectivity. Furthermore, we are optimistic that we can improve the AR bandwidth in the future research using antenna–filter integration that can control a bandwidth.

V. CONCLUSION

A new method for developing a circularly polarized antenna adapting a second-order filtering antenna has been demonstrated. The integration of orthogonal surface current in

TABLE I
COMPARISON WITH PREVIOUS CP FILTERING ANTENNA

Ref.	Profile	CP Method	Delay/filtering circuit	Gain (dBic)	ARBW (%)
[3]	$0.57\lambda \times 0.6125\lambda \times 0.006\lambda$	Single feed line with truncated radiator	Extra circuit	2.1–2.8	20.5
[12]	$0.77\lambda \times 0.77\lambda \times 0.03\lambda$	Single feed line with truncated radiator	Extra circuit	8	8.5
[13]	$0.91\lambda \times 0.91\lambda \times 0.022\lambda$	Single feed line with radiator perturbation	Extra circuit	8.3	5.3
[14]	$1\lambda \times 1\lambda \times 0.036\lambda$	Single feed line with radiator perturbation	Extra circuit	8	3.9
[16]	$0.53\lambda \times 0.53\lambda \times 0.07\lambda$	Orthogonal feedlines	Extra circuit	5.2	12.5
[17]	$1.06\lambda \times 1.06\lambda \times 0.027\lambda$	Orthogonal feedlines	Extra circuit	5.8	8.8
[18]	$0.72\lambda \times 0.72\lambda \times 0.018\lambda$	Orthogonal feedlines	Extra circuit	6.1	3.8
This work	$0.69\lambda \times 0.69\lambda \times 0.048\lambda$	Single feedline with orthogonal resonators	No extra circuit	6.72	3.2

the rectangular radiator and $\lambda/4$ resonator resulted in a left-hand CP filtering antenna. The radiator's length and width significantly affected the electric field magnitude in θ and ϕ directions. The gap spacing between the rectangular radiator and $\lambda/4$ resonator determined the phase delay. The performance of the conventional filtering antenna and the antenna based on the new method was compared. The proposed method was validated by the agreement between the simulation and measurement results.

ACKNOWLEDGMENT

The authors thank to Anshari and Rosza from Research Center for Satellite Technology—National Research and Innovation Agency, Kevin, Nathan, Dian and Galih from Electrical Engineering Department—Universitas Indonesia for their support in the measurements; Telecommunication Laboratory of Electrical Engineering Department—Faculty of Engineering Universitas Indonesia for providing the measurement laboratory and CST software; and Arry Yanuar for assisting with data sorting.

REFERENCES

- [1] F. N. Ayoub, Y. Tawk, E. Ardelean, J. Costantine, S. Lane, and C. G. Christodoulou, "Cross-Slotted Waveguide Array with Dual Circularly Polarized Radiation at W-Band," *IEEE Transaction on Antennas and Propagation*, vol. 70, no. 1, pp. 268–277, 2022, doi: 10.1109/TAP.2021.3090863.
- [2] E. T. Rahardjo, S. Kitao, and M. Haneishi, "Circularly polarized planar antenna excited by cross-slot coupled coplanar waveguide feedline," *IEEE Antennas and Propagation Society, AP-S International Symposium (Digest)*, vol. 3, pp. 2220–2223, 1994, doi: 10.1109/aps.1994.408042.
- [3] W. Cheng and D. Li, "Circularly polarised filtering monopole antenna based on miniaturised coupled filter," *Electron Lett*, vol. 53, no. 11, pp. 11–12, 2017, doi: 10.1049/el.2017.1094.
- [4] T. Li and X. Gong, "Vertical Integration of High-Q Filter with Circularly Polarized Patch Antenna with Enhanced Impedance-Axial Ratio Bandwidth," *IEEE Trans Microw Theory Tech*, vol. 66, no. 6, pp. 3119–3128, 2018, doi: 10.1109/TMTT.2018.2832073.
- [5] N. Hussain, G. S. Member, and M. Jeong, "Metasurface-Based Single-Layer Wideband Circularly Polarized MIMO Antenna for 5G Millimeter-Wave Systems," *IEEE Access*, vol. 8, pp. 130293–130304, 2020, doi: 10.1109/ACCESS.2020.3009380.
- [6] C. E. Santosa, J. T. S. Sumantyo, S. Gao, and K. Ito, "Broadband Circularly Polarized Microstrip Array Antenna with Curved-Truncation and Circle-Slotted Parasitic," *IEEE Trans Antennas Propag*, vol. 69, no. 9, pp. 5524–5533, 2021, doi: 10.1109/TAP.2021.3060122.
- [7] S. Maddio, G. Pelosi, and S. Selleri, "Circularly polarised sequential array with enhanced gain and bandwidth for applications in C-band," *IET Microw. Antennas Propag*, vol. 14, no. 15, pp. 1926–1932, 2020, doi: 10.1049/iet-map.2020.0450.
- [8] M. K. Ray, K. Mandal, N. Nasimuddin, A. Lalbakhsh, R. Raad, and F. Tabbul, "Two-Pair Slots Inserted CP Patch Antenna for Wide Axial Ratio Beamwidth," *IEEE Access*, vol. 8, pp. 223316–223324, 2020, doi: 10.1109/ACCESS.2020.3043406.
- [9] Y. En, "A Wideband Circularly Polarized Microstrip Antenna With Multiple Modes," *IEEE Open Journal of Antennas and Propagation*, vol. 1, no. June, pp. 413–418, 2020, doi: 10.1109/OJAP.2020.3009884.
- [10] U. Ullah, M. Al-Hasan, S. Koziel, and I. Ben Mabrouk, "Series-Slot-Fed Circularly Polarized Multiple-Input-Multiple-Output Antenna Array Enabling Circular Polarization Diversity for 5G 28-GHz Indoor Applications," *IEEE Trans Antennas Propag*, no. 112612, pp. 1–1, 2021, doi: 10.1109/tap.2021.3066247.
- [11] C. Zhou, B. Wang, and H. Wong, "A Compact Dual-Mode Circularly Polarized Antenna with Frequency Reconfiguration," *IEEE Antennas Wirel Propag Lett*, vol. 1225, no. c, pp. 1–5, 2021, doi: 10.1109/LAWP.2021.3073417.
- [12] Y. Dong *et al.*, "Broadband circularly polarized filtering antennas," *IEEE Access*, vol. 6, pp. 76302–76312, 2018, doi: 10.1109/ACCESS.2018.2883494.
- [13] W.-J. Yang, Y.-M. Pan, and X.-Y. Zhang, "A Single-Layer Low-Profile Circularly Polarized Filtering Patch Antenna," *IEEE Antennas Wirel Propag Lett*, vol. 20, no. 4, pp. 602–606, 2021.
- [14] S. Ji, Y. Dong, Y. Pan, Y. Zhu, and Y. Fan, "Planar Circularly Polarized Antenna with Bandpass Filtering Response Based on Dual-Mode SIW Cavity," *IEEE Trans Antennas Propag*, vol. 69, no. 6, pp. 3155–3164, 2021, doi: 10.1109/TAP.2020.3037819.
- [15] M. K. Khandelwal, S. Kumar, and B. K. Kanaujia, "Design, modeling and analysis of dual-feed defected ground microstrip patch antenna with wide axial ratio bandwidth," *J Comput Electron*, vol. 17, no. 3, pp. 1019–1028, 2018, doi: 10.1007/s10825-018-1173-1.
- [16] Z. H. Jiang and D. H. Werner, "A Compact, Wideband Circularly Polarized Co-designed Filtering Antenna and Its Application for Wearable Devices With Low SAR," *IEEE Trans Antennas Propag*, vol. 63, no. 9, pp. 3808–3818, 2015, doi: 10.1109/TAP.2015.2452942.
- [17] Q. Wu, X. Zhang, and L. Zhu, "Co-Design of a Wideband Circularly Polarized Filtering Patch Antenna With Three Minima in Axial Ratio Response," *IEEE Trans Antennas Propag*, vol. 66, no. 10, pp. 5022–5030, 2018, doi: 10.1109/TAP.2018.2856104.
- [18] W. Wang, C. Chen, S. Wang, and W. Wu, "Circularly Polarized Patch Antenna With Filtering Performance Using Polarization Isolation and Dispersive Delay Line," *IEEE Antennas Wirel Propag Lett*, vol. 19, no. 8, pp. 1457–1461, 2020.
- [19] H. Wenjia and Y. Horii, "Enhanced Group Delay of Microstrip-Line-Based Dispersive Delay Lines with LC Resonant Circuits For Real-Time Analog Signal Processing," in *Asia Pacific Microwave Conference, APMC*, 2017, pp. 273–275.

> REPLACE THIS LINE WITH YOUR MANUSCRIPT ID NUMBER (DOUBLE-CLICK HERE TO EDIT) <

- [20] R. Kumar and K. J. Vinoy, "Large Group Delay in Microstrip Circuit Using Coupled Open Stubs and Collocated Ground Slots," *IEEE Microwave and Wireless Components Letters*, vol. 30, no. 6, pp. 553–556, Jun. 2020, doi: 10.1109/LMWC.2020.2992104.
- [21] Z. Wang, Y. Meng, S. Fang, and H. Liu, "Wideband Flat Negative Group Delay Circuit With Improved Signal Attenuation," *IEEE Transactions on Circuits and Systems II: Express Briefs*, vol. 69, no. 8, pp. 3371–3375, Aug. 2022, doi: 10.1109/TCSII.2022.3156537.
- [22] G. Chaudhary and Y. Jeong, "Synthesis of Reflection-Type Coupled Line All-Pass Circuit with Arbitrary Prescribed Wideband Flat Group Delay," *IEEE Microwave and Wireless Components Letters*, vol. 27, no. 10, pp. 876–878, Oct. 2017, doi: 10.1109/LMWC.2017.2747149.
- [23] B. Ravelo, "Negative Group-Delay Phenomenon Analysis With Distributed Parallel Interconnect Line," *IEEE Trans Electromagn Compat*, vol. 58, no. 2, pp. 573–580, Apr. 2016, doi: 10.1109/TEMC.2016.2516899.
- [24] T. Shao, Z. Wang, S. Fang, H. Liu, and Z. N. Chen, "A full-passband linear-phase band-pass filter equalized with negative group delay circuits," *IEEE Access*, vol. 8, pp. 43336–43343, 2020, doi: 10.1109/ACCESS.2020.2977100.
- [25] T. Zhang, T. Yang, and P. L. Chi, "Novel Reconfigurable Negative Group Delay Circuits with Independent Group Delay and Transmission Loss/Gain Control," *IEEE Trans Microw Theory Tech*, vol. 68, no. 4, pp. 1293–1303, Apr. 2020, doi: 10.1109/TMTT.2019.2955704.
- [26] M. K. Mandal, D. Deslandes, and K. Wu, "Complementary microstrip-slotline stub configuration for group delay engineering," *IEEE Microwave and Wireless Components Letters*, vol. 22, no. 8, pp. 388–390, 2012, doi: 10.1109/LMWC.2012.2205229.
- [27] M. L. N. Chen, L. J. Jiang, and W. E. I. Sha, "Artificial Perfect Electric Conductor-Perfect Magnetic Conductor Anisotropic," *Appl Phys A Mater Sci Process*, no. 119, pp. 1–5, 2016.
- [28] Q. Wu, X. Zhang, and L. Zhu, "A Feeding Technique for Wideband CP Patch Antenna Based on 90 ° Phase Difference Between Tapped Line and Parallel Coupled Line," *IEEE Antennas Wirel Propag Lett*, vol. 18, no. 7, pp. 1468–1471, 2019.
- [29] Q. Sen Wu, X. Zhang, and L. Zhu, "A Wideband Circularly Polarized Patch Antenna With Enhanced Axial Ratio Bandwidth via Co-Design of Feeding Network," *IEEE Trans Antennas Propag*, vol. 66, no. 10, pp. 4996–5003, 2018, doi: 10.1109/TAP.2018.2851616.
- [30] D. A. Cahyasiwi, F. Y. Zulkifli, and E. T. Rahardjo, "Stacked Interdigital Filtering Antenna with Slant Polarization," in *Conference on Antenna Measurement and Application*, 2019, pp. 275–278.
- [31] D. A. Cahyasiwi, F. Y. Zulkifli, and E. T. Rahardjo, "Switchable Slant Polarization Filtering Antenna Using Two Inverted Resonator Structures for 5G Application," *IEEE Access*, vol. 8, pp. 224033–224043, 2020, doi: 10.1109/ACCESS.2020.3043824.
- [32] D. A. Cahyasiwi, E. Roza, M. Mujirudin, N. M. Nashuha, F. Y. Zulkifli, and E. T. Rahardjo, "Selectivity improvement of interdigital filtering-antenna using different orders for 5 G application," *Int J Microw Wirel Technol*, pp. 1–9, Nov. 2022, doi: 10.1017/S1759078722001143.
- [33] W. Stutzman and G. Thiele, *Antenna Theory and Design*, Third ed. Third ed. NJ, USA: John Wiley & Sons, 2013.

AUTHOR BIOGRAPHIES



Dwi Astuti Cahyasiwi (Member, IEEE) received her Bachelor, Magister, and Doctoral degree in Electrical Engineering from the Universitas Indonesia in 1997, 2009, 2022. She received Excellent Scholarship for Indonesia's Lecture (Beasiswa Unggulan Dosen Indonesia/BUDI-LPDP) for her Doctoral degree. She is a member of IEEE Antenna and Propagation Society (AP-S) since 2021 and a reviewer of IEEE Access since 2020. Cahyasiwi was a recipient of the Best Student Paper Award at the 2019 IEEE Conference on Antenna Measurement and Applications (CAMA). She has been a lecture in Electrical Engineering Department Universitas Muhammadiyah Prof Dr HAMKA since 2000. Her research interests are integration design of antenna and filter, multiple-input multiple-output (MIMO) antenna, dual-polarized antenna systems, metasurface, polarization converter and microwave circuits.



Fitri Yuli Zulkifli (Senior Member IEEE) received her Bachelor and Ph.D. degrees in Electrical Engineering from Universitas Indonesia (UI) in 1997 and 2009, while M.Sc. degree from Karlsruhe Institute of Technology, Germany in 2002. Her research interests are antenna, propagation, microwave, and in the field of telecommunication. She joined the Antenna Propagation and Microwave Research Group (AMRG) UI since 1997 and has become lecturer in Electrical Engineering Department UI since 1998. Prof. Yuli has published more than 200 papers in journals/conference proceedings and received more than 40 research grants. She now leads "Laboratory Prof. Fitri Yuli Zulkifli" and also the head of professional engineering study program in UI. From 2011 to 2012 she became the joint chapter chair of MTT/AP Indonesia. In 2017–2018, she was the IEEE Indonesia Section Chair and from 2019 to 2022, she has been serving as a committee member for R10 Conference and Technical Seminar and Conference Quality Management.

> REPLACE THIS LINE WITH YOUR MANUSCRIPT ID NUMBER (DOUBLE-CLICK HERE TO EDIT) <



Eko Tjipto Rahardjo. (Member, IEEE) received B. Eng. degree from Universitas Indonesia, Indonesia, in 1981, the M.S. degree from the University of Hawaii, USA, in 1987, and the Ph.D. degree from Saitama University, Japan, in 1996, all in Electrical Engineering. He has been the Director of Antenna Propagation and Microwave Research Group (AMRG), Universitas Indonesia. His research interests include antenna engineering, wave propagation, microwave circuits and communication systems, and telecommunication system regulations. He has published and presented more than 200 research articles both in national and international journals and symposiums. Prof. Rahardjo is a member of the IEEE Antenna and Propagation Society (AP-S) and the IEEE Microwave Theory and Technique Society (MTTS) and has been actively participating in the National and International Committee as the International Advisory Board, Steering Committee, or General Chair in the International Symposium on Antenna and Propagation (ISAP), Asia Pacific Microwaves Conference (APMC), and IEEE Conference on Antenna Measurement and Applications (CAMA)

Dwi Astuti Cahyasiwi - Orthogonal Resonators for Circularly Polarized Filtering Antenna Using A Single Feedline

ORIGINALITY REPORT

16%

SIMILARITY INDEX

8%

INTERNET SOURCES

14%

PUBLICATIONS

3%

STUDENT PAPERS

PRIMARY SOURCES

- | | | |
|---|---|----|
| 1 | Submitted to Universiti Teknikal Malaysia Melaka
Student Paper | 2% |
| 2 | Dwi Astuti Cahyasiwi, Emilia Roza, Mohammad Mujirudin, Nusriyati Mahmuda Nashuha, Fitri Yuli Zulkifli, Eko Tjipto Rahardjo. "Selectivity improvement of interdigital filtering-antenna using different orders for 5 G application", International Journal of Microwave and Wireless Technologies, 2022
Publication | 2% |
| 3 | Dwi Astuti Cahyasiwi, Fitri Yuli Zulkifli, Eko Tjipto Rahardjo. "Switchable Slant Polarization Filtering Antenna Using Two Inverted Resonator Structures for 5G Application", IEEE Access, 2020
Publication | 2% |
| 4 | www.researchgate.net
Internet Source | 1% |
-

5	Dwi Astuti Cahyasiwi, Fitri Yuli Zulkifli, Eko Tjipto Rahardjo. "Stacked Interdigital Filtering Antenna with Slant Polarization", 2019 IEEE Conference on Antenna Measurements & Applications (CAMA), 2019 Publication	1 %
6	www.scirp.org Internet Source	<1 %
7	core.ac.uk Internet Source	<1 %
8	Arie Pangesti Aji, Catur Apriono, Eko Tjipto Rahardjo. "Input Power and Effective Area in Terahertz Detector Measurement: A Review", IEEE Access, 2023 Publication	<1 %
9	researchmap.jp Internet Source	<1 %
10	www.meteorama.fr Internet Source	<1 %
11	Submitted to University of Macau Student Paper	<1 %
12	Hui Chu, Hong Hong, Xiaohua Zhu, Yong-Xin Guo, Peng Li. "Implementation of Synthetic Material in Dielectric Resonator Based Filtering Antennas", IEEE Transactions on Antennas and Propagation, 2018	<1 %

13

Qiong-Sen Wu, Xiao Zhang, Lei Zhu. "Co-design of a Wideband Circularly Polarized Filtering Patch Antenna with Three Minima in Axial Ratio Response", IEEE Transactions on Antennas and Propagation, 2018

Publication

<1 %

14

Devisowjanya Potti, Savarimuthu Kirubaveni, G. Sudhilaya, Mohammed Gulam Nabi Alsath, S. Radha. "Thin film based optically transparent circular monopole antenna for wideband applications", Analog Integrated Circuits and Signal Processing, 2021

Publication

<1 %

15

T. Euler, J. Papapolymerou. "A novel micromachined planar filter on Si substrate at 45 GHz based on electromagnetic bandgap structures for wireless applications", 2003 Topical Meeting on Silicon Monolithic Integrated Circuits in RF Systems, 2003. Digest of Papers., 2003

Publication

<1 %

16

repository.mercubuana.ac.id

Internet Source

<1 %

17

Aashish Kumar, Chandra Shekhar Rai, Mukesh Kumar Khandelwal. "Omnidirectional circularly polarized 4-port MIMO antennas with minimum cross-polarization for 5G

<1 %

applications", 2021 IEEE Madras Section
Conference (MASCON), 2021

Publication

18

Bo Wei Xu, Bing Jie Xiang, Shao Yong Zheng.
"Wideband Circularly Polarized Filtering
Antenna Based on Metasurface", 2018
International Conference on Microwave and
Millimeter Wave Technology (ICMMT), 2018

Publication

<1 %

19

Shuxuan Liu, Zhan Wang, Yuandan Dong. "A
Compact Filtering Patch Antenna with High
Suppression Level and Its CP Application",
IEEE Antennas and Wireless Propagation
Letters, 2022

Publication

<1 %

20

[insightsociety.org](https://www.insightsociety.org)

Internet Source

<1 %

21

pureadmin.qub.ac.uk

Internet Source

<1 %

22

small-antennas.eu

Internet Source

<1 %

23

www.rc-group.ru

Internet Source

<1 %

24

Lei Li, Shi xuan Wu, Di Pang, Xiao lin Zhang,
Qing Wang. "A Fifth-order Single-Layer Dual-
Frequency Half-Mode SIW Filtering Antenna

<1 %

With Multifunction Single Slot", IEEE Antennas and Wireless Propagation Letters, 2021

Publication

25

doaj.org
Internet Source

<1 %

26

downloads.hindawi.com
Internet Source

<1 %

27

stars.library.ucf.edu
Internet Source

<1 %

28

"Optical and Wireless Technologies", Springer Science and Business Media LLC, 2020
Publication

<1 %

29

Ghanshyam Singh, Sachin Kumar, Binod Kumar Kanaujia, Vijay Kumar Pandey, Ajay Abrol. "Compact Modified Electric-Inductive-Capacitive Inspired Antenna for Triple-Band Operation", 2021 10th International Conference on Internet of Everything, Microwave Engineering, Communication and Networks (IEMECON), 2021
Publication

<1 %

30

Hongmei Liu, Jiahui Wang, Zimeng Zhao, Zhongbao Wang, Shaojun Fang. "Design of Wideband GNSS Antenna with Wide-Angle Circular Polarization and Anti-Multipath Performance for High Precision Marine

<1 %

Positioning", IEEE Transactions on Vehicular Technology, 2022

Publication

31

Huayan Jin, Shanshan Nie, Wenlei Wang, Kuo - Sheng Chin, Liang Peng, Guo Q. Luo. "A broadband single - fed circularly polarized patch filtenna with high suppression level", Microwave and Optical Technology Letters, 2022

Publication

32

Ningning Yan, Kaixue Ma, Yu Luo. "An SISL Sequentially Rotated Feeding Circularly Polarized Stacked Patch Antenna Array", IEEE Transactions on Antennas and Propagation, 2020

Publication

33

Zeng-Pei Zhong, Xiao Zhang. "A Travelling-Wave-Fed Slot Spiral Antenna with Wide Axial-Ratio Bandwidth and Beamwidth for GNSS Applications", IEEE Open Journal of Antennas and Propagation, 2021

Publication

34

[aces-society.org](https://www.aces-society.org)

Internet Source

35

[ictactjournals.in](https://www.ictactjournals.in)

Internet Source

36

www.jocm.us

Internet Source

<1 %

<1 %

<1 %

<1 %

<1 %

<1 %

37

"Technical programme", 2017 IEEE Asia Pacific Microwave Conference (APMC), 2017

Publication

<1 %

38

Gen-Zhu Liang, Fu-Chang Chen, Hang Yuan, Kai-Ran Xiang, Qing-Xin Chu. "A High Selectivity and High Efficiency Filtering Antenna With Controllable Radiation Nulls Based on Stacked Patches", IEEE Transactions on Antennas and Propagation, 2022

Publication

<1 %

39

Bambang Dewandaru, Fitri Yuli Zulkifli, Eko Tjipto Rahardjo. "Complementary Interleaved CDS Arrays to Improve Antenna Aperture Utilization", International Journal on Communications Antenna and Propagation (IRECAP), 2019

Publication

<1 %

40

Teguh Firmansyah, Mudrik Alaydrus, Yuyu Wahyu, Eko Tjipto Rahardjo, Gunawan Wibisono. "A highly independent multiband bandpass filter using a multi-coupled line stub-SIR with folding structure", IEEE Access, 2020

Publication

<1 %

41

Tianjiao Li, Xun Gong. "Vertical Integration of High-Q Filter With Circularly Polarized Patch Antenna With Enhanced Impedance-Axial Ratio Bandwidth", IEEE Transactions on Microwave Theory and Techniques, 2018

Publication

<1 %

42

Zhipeng Zhao, Feng Liu, Jian Ren, Ying Liu, yingzeng Yin. "Dual-Sense Circularly Polarized Antenna with A Coupled Line", IEEE Antennas and Wireless Propagation Letters, 2020

Publication

<1 %

Exclude quotes Off

Exclude matches Off

Exclude bibliography On